INA203-Q1 采用两个比较器和基准的汽车级、-16 V 至 +80 V、低侧或高侧、高速电压输出分流监测计

1 特性

- 汽车电子 应用认证
- 电流感测放大器
  - 共模范围：-16V 至 +80V
  - 精度：整个温度范围内的精度为 3.5%（最大值）
  - 带宽：500 kHz
  - 增益：20V/V
- 集成双比较器：
  - 具有锁存功能的比较器 1
  - 延迟可选的比较器 2
- 静态电流：1.8mA
- 锁存性能可达 100mA，符合 AEC-Q100 I 级标准
- 封装：薄型小外形尺寸 (TSSOP)-14

2 应用

- 电动助力转向 (EPS) 系统
- 车身控制模块
- 刹车系统
- 电子稳定性控制 (ESC) 系统

3 说明

INA203-Q1 是一款单向分流监测计（也称电流感测放大器），具备电压输出、两个比较器和电压基准。INA203-Q1 能够在 -16V 至 +80V 范围内的共模电压下感测分流器两端的压降。INA203-Q1 的增益为 20V/V，带宽高达 500kHz。

INA203-Q1 采用两个开漏比较器及 0.6V 内部基准，还可提供 1.2V 基准输出。比较器基准可由外部输入替代。比较器 1 具备锁存功能，而比较器 2 的延迟可由用户通过编程设定。


INA203-Q1 由 2.7V 至 18V 单电源供电。该器件可在 -40°C 至 +125°C 扩展工作温度范围内额定运行。

器件信息(1)

器件型号	封装	封装尺寸（标称值）
INA203-Q1	TSSOP (14)	5.00mm x 4.40mm

(1) 要了解所有可用封装，请见数据表末尾的可订购产品附录。

基础连接电路原理图



Copyright © 2016, Texas Instruments Incorporated

目录

1 特性 ... 1
2 应用 ... 1
3 说明 ... 1
4 修订历史记录 ... 2
5 **Device Comparison Table** ... 3
6 **Pin Configuration and Functions** ... 3
7 **Specifications** ... 4
7.1 Absolute Maximum Ratings ... 4
7.2 ESD Ratings ... 4
7.3 Recommended Operating Conditions ... 4
7.4 Thermal Information ... 4
7.5 Electrical Characteristics: Current-Shunt Monitor ... 5
7.6 Electrical Characteristics: Comparator ... 6
7.7 Electrical Characteristics: Reference ... 7
7.8 Electrical Characteristics: General ... 7
7.9 Typical Characteristics ... 8
8 **Detailed Description** ... 12
8.1 Overview ... 12
8.2 Functional Block Diagram ... 12
8.3 Feature Description ... 12
8.4 Device Functional Modes ... 14
9 **Application and Implementation** ... 15
9.1 Application Information ... 15
9.2 Typical Applications ... 19
10 **Power Supply Recommendations** ... 21
11 **Layout** ... 21
11.1 Layout Guidelines ... 21
11.2 Layout Example ... 21
12 器件和文档支持 ... 22
12.1 社区资源 ... 22
12.2 商标 ... 22
12.3 静电放电警告 ... 22
12.4 Glossary ... 22
13 机械、封装和可订购信息 ... 22

4 修订历史记录

注：之前版本的页码可能与当前版本有所不同。

Changes from Original (December 2010) to Revision A **Page**

- 已更新数据表标题， *特性*, *应用*, 和 *说明* ... 1
- 已添加 *ESD 额定值*表，*特性 描述*部分，*器件功能模式*，*应用和实施*部分，*电源相关建议*部分，*布局*部分，*器件和文档支持*部分，*机械、封装和可订购信息*部分，*引脚配置和功能*部分，*建议运行条件*表以及*热性能信息*表 ... 1
- Added *Device Comparison Table* ... 3
- Changed V+ to V_S throughout ... 4
- Changed MAX value 18 to (V_S) + 0.3 for Comparator output pins ... 4
- Changed MAX value 10 to (V_S) up to 10 for 1.2-V REF and CMP2 DELAY pins ... 4
- Changed pin names in *Absolute Maximum Ratings* to show correct names ... 4
- Added Operating Temperature to *Absolute Maximum Ratings* table ... 4
- Changed CMP2 IN– to CMP2 IN+ in *Electrical Characteristics: Current-Shunt Monitor* condition statement ... 5
- Changed CMP2 IN– to CMP2 IN+ in *Electrical Characteristics: General* condition statement ... 7
- Updated *Overview* section ... 12
- Deleted 10-pin device image ... 12
- Changed text from "RFILT – 3%" to "RFILT + 3%" in 2nd paragraph of *Input Filtering* section ... 16
- Changed Figure 35 caption ... 16

Copyright © 2010–2016, Texas Instruments Incorporated


5 Device Comparison Table

Table 1. Related Products

PRODUCT	DESCRIPTION
INA200–Q1	Single comparator alternative to the INA203's dual comparators
INA193A–Q1	Same amplifier performance without the comparators integrated
INA282–Q1	High-accuracy, high common-mode capable current sense amplifier
INA300–Q1	36-V overcurrent protection comparator
INA301	High-accuracy, high slew-rate current sense amplifier with integrated high-speed comparator optimized for overcurrent protection.

6 Pin Configuration and Functions

PW Package
14-Pin TSSOP
Top View



Pin Functions

PIN		I/O	DESCRIPTION
NO.	NAME		
1	V_S	I	Power supply
2	OUT	O	Output voltage
3	CMP1 IN-/0.6-V REF	I	Comparator 1 negative input, can be used to override the internal 0.6-V reference
4	CMP1 IN+	I	Comparator 1 positive input
5	CMP2 IN+	I	Comparator 2 positive input
6	CMP2 IN–/0.6-V REF	I	Comparator 2 negative input, can be used to override the internal 0.6-V reference
7	GND	I	Ground
8	CMP1 $\overline{\text{RESET}}$	I	Comparator 1 ouput reset, active low
9	CMP2 DELAY	I	Connect an optional capacitor to adjust comparator 2 delay
10	CMP2 OUT	O	Comparator 2 output
11	CMP1 OUT	O	Comparator 1 output
12	1.2-V REF OUT	O	1.2-V reference output
13	$V_{IN–}$	I	Amplifier Negative Input. Connect to shunt low side
14	V_{IN+}	I	Amplifier Positive Input. Connect to shunt high side

Copyright © 2010–2016, Texas Instruments Incorporated

7 Specifications

7.1 Absolute Maximum Ratings

over operating free-air temperature range (unless otherwise noted) (1)

		MIN	MAX	UNIT
Supply voltage	V_S		18	V
Current-shunt monitor analog inputs, V_{IN+} and V_{IN-}	Differential (V_{IN+}) – (V_{IN-})	–18	18	V
	Common-mode	–16	80	V
Comparator analog input	CMP1 IN+, CMP1 IN-/0.6-V REF, CMP2 IN+, CMP2 IN-/0.6-V REF	GND – 0.3	(V_S) + 0.3	V
Comparator reset	CMP1 $\overline{\text{RESET}}$	GND – 0.3	(V_S) + 0.3	
Analog output	OUT	GND – 0.3	(V_S) + 0.3	V
Comparator output	CMP1 OUT, CMP2 OUT	GND – 0.3	(V_S) + 0.3	V
1.2-V REF and CMP2 DELAY pins		GND – 0.3	(V_S) up to 10	V
Input current into any pin			5	mA
Operating temperature		–55	150	°C
Junction temperature			150	°C
Storage temperature, T_{stg}		–65	150	°C

(1) Stresses beyond those listed under *Absolute Maximum Ratings* may cause permanent damage to the device. These are stress ratings only, which do not imply functional operation of the device at these or any other conditions beyond those indicated under *Recommended Operating Conditions*. Exposure to absolute-maximum-rated conditions for extended periods may affect device reliability.

7.2 ESD Ratings

			VALUE	UNIT
$V_{(ESD)}$	Electrostatic discharge	Human-body model (HBM), per AEC Q100-002 (1)	±2000	V
		Charged-device model (CDM), per AEC Q100-011	±500	

(1) AEC Q100-002 indicates that HBM stressing shall be in accordance with the ANSI/ESDA/JEDEC JS-001 specification.

7.3 Recommended Operating Conditions

over operating free-air temperature range (unless otherwise noted)

		MIN	NOM	MAX	UNIT
V_{CM}	Common-mode input voltage	–16	12	80	V
V_S	Operating supply voltage	2.7	12	18	V
T_A	Operating free-air temperature	–40	25	125	ºC

7.4 Thermal Information

THERMAL METRIC (1)		INA203-Q1 PW (TSSOP) 14 PINS	UNIT
$R_{\theta JA}$	Junction-to-ambient thermal resistance	112.6	°C/W
$R_{\theta JC(top)}$	Junction-to-case (top) thermal resistance	37.2	°C/W
$R_{\theta JB}$	Junction-to-board thermal resistance	55.4	°C/W
ψ_{JT}	Junction-to-top characterization parameter	2.7	°C/W
ψ_{JB}	Junction-to-board characterization parameter	54.7	°C/W
$R_{\theta JC(bot)}$	Junction-to-case (bottom) thermal resistance	150	°C/W

(1) For more information about traditional and new thermal metrics, see the *Semiconductor and IC Package Thermal Metrics* application report, SPRA953.

Copyright © 2010–2016, Texas Instruments Incorporated

7.5 Electrical Characteristics: Current-Shunt Monitor

At T_A = 25°C, V_S = 12 V, V_{CM} = 12 V, V_{SENSE} = 100 mV, R_L = 10 kΩ to GND, $R_{PULL-UP}$ = 5.1 kΩ each connected from CMP1 OUT and CMP2 OUT to V_S, and CMP1 IN+ = 1 V and CMP2 IN+ = GND, unless otherwise noted.

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
INPUT							
V_{SENSE}	Full-scale sense input voltage	$V_{SENSE} = V_{IN+} - V_{IN-}$			0.15	(V_S – 0.25)/Gain	V
V_{CM}	Common-mode input range	T_A = –40°C to +125°C		–16		80	V
CMRR	Common-mode rejection ratio	V_{CM} = –16 V to +80 V		80	100		dB
	Over temperature	V_{CM} = 12 V to 80 V	T_A = 25°C to 125°C	100	123		dB
		T_A = –40°C to +25°C		90	100		dB
V_{OS}	Offset voltage, RTI[1]				±0.5	±2.5	mV
		T_A = 25°C to 125°C				±3	mV
		T_A = –40°C to +25°C				±3.5	mV
dV_{OS}/dT	Versus temperature	T_{MIN} to T_{MAX}	T_A = –40°C to +125°C		5		µV/°C
PSR	Versus power supply	V_{OUT} = 2 V, V_{CM} = +18 V	T_A = –40°C to +125°C		2.5	100	µV/V
I_B	Input bias current, V_{IN-} Pin	T_A = –40°C to +125°C			±9	±16	µA
OUTPUT (V_{SENSE} ≥ 20 mV)							
G	Gain				20		V/V
	Gain error	V_{SENSE} = 20 mV to 100 mV			±0.2%	±1%	
	Over temperature	V_{SENSE} = 20 mV to 100 mV	T_A = –40°C to +125°C			±2%	
	Total output error[2]	V_{SENSE} = 120 mV, V_S = +16 V			±0.75%	±2.2%	
	Over temperature	V_{SENSE} = 120 mV, V_S = +16 V	T_A = –40°C to +125°C			±3.5%	
	Nonlinearity error[3]	V_{SENSE} = 20 mV to 100 mV			±0.002%		
R_O	Output impedance, Pin 2				1.5		Ω
	Maximum capacitive load	No sustained oscillation			10		nF
OUTPUT (V_{SENSE} < 20 mV)[4]							
V_{OUT}	Output voltage	–16 V ≤ V_{CM} < 0 V			300		mV
		0 V ≤ V_{CM} ≤ V_S, V_S = 5 V				0.4	V
		V_S < V_{CM} ≤ 80 V			300		mV
VOLTAGE OUTPUT[5]							
	Output swing to the positive rail	V_{IN-} = 11 V, V_{IN+} = 12 V	T_A = –40°C to +125°C		(V_S) – 0.15	(V_S) – 0.25	V
	Output Swing to GND[6]	V_{IN-} = 0 V, V_{IN+} = –0.5 V	T_A = –40°C to +125°C		(V_{GND}) + 0.004	(V_{GND}) + 0.05	V
FREQUENCY RESPONSE							
BW	Bandwidth	C_{LOAD} = 5 pF			500		kHz
	Phase margin	C_{LOAD} < 10 nF			40		Degrees
SR	Slew rate				1		V/µs
	Settling time (1%)	V_{SENSE} = 10 mV_{PP} to 100 mV_{PP}, C_{LOAD} = 5 pF			2		µs
NOISE, RTI							
	Output Voltage Noise Density				40		nV/√Hz

(1) Offset is extrapolated from measurements of the output at 20 mV and 100 mV V_{SENSE}.
(2) Total output error includes effects of gain error and V_{OS}.
(3) Linearity is best fit to a straight line.
(4) For details on this region of operation, see the *Accuracy Variations* section.
(5) See *Typical Characteristics* curve *Positive Output Voltage Swing vs Output Current* (Figure 8).
(6) Specified by design; not production tested.

Copyright © 2010–2016, Texas Instruments Incorporated

7.6 Electrical Characteristics: Comparator

At T_A = +25°C, V_S = +12 V, V_{CM} = +12 V, V_{SENSE} = 100 mV, R_L = 10 kΩ to GND, and $R_{PULL-UP}$ = 5.1 kΩ each connected from CMP1 OUT and CMP2 OUT to V_S, unless otherwise noted.

PARAMETER	TEST CONDITIONS	MIN	TYP	MAX	UNIT
OFFSET VOLTAGE					
Offset voltage	Comparator common-mode voltage = threshold voltage		2		mV
Offset voltage drift, comparator 1	T_A = –40°C to +125°C		±2		µV/°C
Offset voltage drift, comparator 2	T_A = –40°C to +125°C		5.4		µV/°C
Threshold	Rising Edge on Non-Inverting input, T_A = +25°C	590	608	620	mV
Over temperature	T_A = –40°C to +125°C	586		625	mV
Hysteresis(1), CMP1	T_A = –40°C to +85°C		–8		mV
Hysteresis(1), CMP2	T_A = –40°C to +85°C		8		mV
INPUT BIAS CURRENT(2)					
CMP1 IN+, CMP2 IN+			0.005	10	nA
Over temperature	T_A = –40°C to +125°C			15	nA
INPUT IMPEDANCE					
Pins 3 and 6			10		kΩ
INPUT RANGE					
CMP1 IN+ and CMP2 IN+			0 V to V_S – 1.5 V		V
Pins 3 and 6(3)			0 V to V_S – 1.5 V		V
OUTPUT					
Large-signal differential voltage gain	CMP V_{OUT} 1 V to 4 V, R_L ≥ 15 kΩ connected to 5 V		200		V/mV
High-level output current	V_{ID} = 0.4 V, V_{OH} = V_S		0.0001	1	µA
Low-level output voltage	V_{ID} = –0.6 V, I_{OL} = 2.35 mA		220	300	mV
RESPONSE TIME(4)					
Comparator 1	R_L to 5 V, C_L = 15 pF, 100 mV input step with 5 mV overdrive		1.3		µs
Comparator 2	R_L to 5 V, C_L = 15 pF, 100 mV input step with 5 mV overdrive, C_{DELAY} pin open		1.3		µs
RESET					
RESET threshold(5)			1.1		V
Logic input impedance			2		MΩ
Minimum RESET pulse width			1.5		µs
RESET propagation delay			3		µs
Comparator 2 delay equation(6)			C_{DELAY} = t_D/5		µF
t_D Comparator 2 delay	C_{DELAY} = 0.1 µF		0.5		s

(1) Hysteresis refers to the threshold (the threshold specification applies to a rising edge of a noninverting input) of a falling edge on the noninverting input of the comparator; refer to Figure 1.
(2) Specified by design; not production tested.
(3) See the *Comparator Maximum Input Voltage Range* section.
(4) The comparator response time specified is the interval between the input step function and the instant when the output crosses 1.4 V.
(5) The CMP1 $\overline{\text{RESET}}$ input has an internal 2 MΩ (typical) pull-down. Leaving the CMP1 $\overline{\text{RESET}}$ open results in a LOW state, with transparent comparator operation.
(6) The Comparator 2 delay applies to both rising and falling edges of the comparator output.

Copyright © 2010–2016, Texas Instruments Incorporated

7.7 Electrical Characteristics: Reference

At T_A = +25°C, V_S = +12 V, V_{CM} = +12 V, V_{SENSE} = 100 mV, R_L = 10 kΩ to GND, and $R_{PULL-UP}$ = 5.1 kΩ each connected from CMP1 OUT and CMP2 OUT to V_S, unless otherwise noted.

PARAMETER		TEST CONDITIONS		MIN	TYP	MAX	UNIT
REFERENCE VOLTAGE							
	1.2 V_{REFOUT} output voltage			1.188	1.2	1.212	V
dV_{OUT}/dT	Reference drift(1)	T_A = –40°C to +85°C			40	100	ppm/°C
0.6 V_{REF}	Output voltage (Pins 3 and 6)				0.6		V
dV_{OUT}/dT	Reference drift(1)	T_A = –40°C to +85°C			40	100	ppm/°C
LOAD REGULATION							
dV_{OUT}/dI_{LOAD}	Sourcing	0 mA < I_{SINK} < 0.5 mA	V_{REFOUT} – 1.2 V		0.4	2	mV/mA
	Sinking		0 mA < I_{SOURCE} < 0.5 mA		0.4		mV/mA
LOAD CURRENT							
I_{LOAD}					1		mA
LINE REGULATION							
dV_{OUT}/dV_S		2.7 V < V_S < 18 V			30		μV/V
CAPACITIVE LOAD							
	Reference output maximum capacitive load	No sustained oscillations			10		nF
OUTPUT IMPEDANCE							
	Pins 3 and 6				10		kΩ

(1) Specified by design; not production tested.

7.8 Electrical Characteristics: General

All specifications at T_A = +25°C, V_S = +12 V, V_{CM} = +12 V, V_{SENSE} = 100 mV, R_L = 10 kΩ to GND, $R_{PULL-UP}$ = 5.1 kΩ each connected from CMP1 OUT and CMP2 OUT to V_S, and CMP1 IN+ = 1 V and CMP2 IN+ = GND, unless otherwise noted.

GENERAL PARAMETERS		CONDITIONS		MIN	TYP	MAX	UNIT
POWER SUPPLY							
V_S	Operating Power Supply	T_A = –40°C to +125°C		2.7		18	V
I_Q	Quiescent current	V_{OUT} = 2 V			1.8	2.2	mA
	Over temperature	V_{SENSE} = 0 mV	T_A = –40°C to +125°C			2.8	mA
	Comparator power-on reset threshold(1)				1.5		V

(1) The INA203-Q1 is designed to power-up with the comparator in a defined reset state as long as CMP1 $\overline{\text{RESET}}$ is open or grounded. The comparator will be in reset as long as the power supply is below the voltage shown here. The comparator assumes a state based on the comparator input above this supply voltage. If CMP1 $\overline{\text{RESET}}$ is high at power-up, the comparator output comes up high and requires a reset to assume a low state, if appropriate.




Figure 1. Comparator Hysteresis

Copyright © 2010–2016, Texas Instruments Incorporated

7.9 Typical Characteristics

All specifications at T_A = +25°C, V_S = +12 V, V_{CM} = +12 V, and V_{SENSE} = 100 mV, unless otherwise noted.




Figure 2. Gain vs Frequency




Figure 3. Gain vs Frequency




Figure 4. Gain Plot




Figure 5. Common-Mode and Power-Supply Rejection vs Frequency




Figure 6. Total Output Error vs V_{SENSE}




Figure 7. Total Output Error vs Common-Mode Voltage

Copyright © 2010–2016, Texas Instruments Incorporated

Typical Characteristics (continued)

All specifications at T_A = +25°C, V_S = +12 V, V_{CM} = +12 V, and V_{SENSE} = 100 mV, unless otherwise noted.




Figure 8. Positive Output Voltage Swing vs Output Current




Figure 9. Quiescent Current vs Output Voltage




Figure 10. Quiescent Current vs Common-Mode Voltage




Figure 11. Output Short-Circuit Current vs Supply Voltage




Figure 12. Step Response




Figure 13. Step Response

Copyright © 2010–2016, Texas Instruments Incorporated

Typical Characteristics (continued)

All specifications at T_A = +25°C, V_S = +12 V, V_{CM} = +12 V, and V_{SENSE} = 100 mV, unless otherwise noted.




Figure 14. Step Response




Figure 15. Comparator V_{OL} vs I_{SINK}




Figure 16. Comparator Trip Point vs Supply Voltage




Figure 17. Comparator Trip Point vs Temperature




Figure 18. Comparator 1 Propagation Delay vs Overdrive Voltage




Figure 19. Comparator 2 Propagation Delay vs Overdrive Voltage

Copyright © 2010–2016, Texas Instruments Incorporated

Typical Characteristics (continued)

All specifications at T_A = +25°C, V_S = +12 V, V_{CM} = +12 V, and V_{SENSE} = 100 mV, unless otherwise noted.




Figure 20. Comparator Reset Voltage vs supply Voltage




Figure 21. Comparator 1 Propagation Delay vs Temperature




Figure 22. Comparator 2 Propagation Delay vs Capacitance




Figure 23. Comparator 1 Propagation Delay




Figure 24. Comparator 2 Propagation Delay




Figure 25. Reference Voltage vs Temperature


Copyright © 2010–2016, Texas Instruments Incorporated

8 Detailed Description

8.1 Overview

The INA203-Q1 device is a unidirectional voltage output current-sense amplifier with dual comparators and voltage reference. The INA203-Q1 operates over a wide range of common-mode voltage (–16 V to +80 V) and incorporates two open-drain comparators with internal 0.6-V references. Comparator 1 includes a latching capability, and Comparator 2 has a user-programmable delay. The device also incorporates a 1.2-V reference output.

8.2 Functional Block Diagram



Copyright © 2016, Texas Instruments Incorporated

8.3 Feature Description

8.3.1 Comparator

The INA203-Q1 incorporates two open-drain comparators. These comparators typically have 2 mV of offset and a 1.3-μs (typical) response time. The output of Comparator 1 latches and is reset through the CMP1 $\overline{\text{RESET}}$ pin, as shown in Figure 26.

The INA203-Q1 device includes additional features for comparator functions. The comparator reference voltage of both Comparator 1 and Comparator 2 can be overridden by external inputs for increased design flexibility. Comparator 2 has a programmable delay.




Figure 26. Comparator Latching Capability

8.3.2 Comparator Delay

The Comparator 2 programmable delay is controlled by a capacitor connected to the CMP2 Delay Pin; see Figure 30. The capacitor value (in μF) is selected by using Equation 1:

$$C_{DELAY}\ (\text{in } \mu F) = \frac{t_D}{5} \quad (1)$$

A simplified version of the delay circuit for Comparator 2 is shown in Figure 27. The delay comparator consists of two comparator stages with the delay between them.

Copyright © 2010–2016, Texas Instruments Incorporated

Feature Description (continued)

NOTE

I1 and I2 cannot be turned on simultaneously; I1 corresponds to a U1 low output and I2 corresponds to a U1 high output.

Using an initial assumption that the U1 output is low, I1 is on, then U2 +IN is zero. If U1 goes high, I2 supplies 120 nA to C_{DELAY}. The voltage at U2 +IN begins to ramp toward a 0.6-V threshold. When the voltage crosses this threshold, the U2 output goes high while the voltage at U2 +IN continues to ramp up to a maximum of 1.2 V when given sufficient time (twice the value of the delay specified for C_{DELAY}). This entire sequence is reversed when the comparator outputs go low, so that returning to low exhibits the same delay.




Figure 27. Simplified Model of The Comparator 2 Delay Circuit

It is important to note the behavior of the Comparator 2 when the events at the inputs occur more rapidly than the set delay timeout. For example, when the U1 output goes high (turning on I2), but returns low (turning I1 back on) prior to reaching the 0.6 V transition for U2. The voltage at U2 +IN ramps back down at a rate determined by the value of C_{DELAY}, and only returns to zero if given sufficient time.


In essence, when analyzing Comparator 2 for behavior with events more rapid than its delay setting, use the model shown in Figure 27.

8.3.3 Comparator Maximum Input Voltage Range

The maximum voltage at the comparator input for normal operation is up to (V_S) – 1.5 V. There are special considerations when overdriving the reference inputs (pins 3 and 6). Driving either or both inputs high enough to drive 1 mA back into the reference introduces errors into the reference. Figure 28 shows the basic input structure. A general guideline is to limit the voltage on both inputs to a total of 20 V. The exact limit depends on the available voltage and whether either or both inputs are subject to the large voltage. When making this determination, consider the 20 kΩ from each input back to the comparator. Figure 29 shows the maximum input voltage that avoids creating a reference error when driving both inputs (an equivalent resistance back into the reference of 10 kΩ).


Copyright © 2010–2016, Texas Instruments Incorporated

Feature Description (continued)



Copyright © 2016, Texas Instruments Incorporated

Figure 28. Limit Current Into Reference ≤ 1 mA



Copyright © 2016, Texas Instruments Incorporated

Figure 29. Overdriving Comparator Inputs Without Generating a Reference Error

8.3.4 Reference

The INA203-Q1 include an internal voltage reference that has a load regulation of 0.4 mV/mA (typical), and not more than 100 ppm/°C of drift. The device allows external access to reference voltages, where voltages of 1.2 V and 0.6 V are both available. Output current versus output voltage is illustrated in the *Typical Characteristics* section.

8.3.5 Output Voltage Range

The output of the INA203-Q1 is accurate within the output voltage swing range set by the power-supply pin, V_S. Given the device gain of 20, where a 250 mV full-scale input from the shunt resistor requires an output voltage swing of +5 V, and a power-supply voltage sufficient to achieve +5 V on the output.

8.4 Device Functional Modes

The INA203-Q1 has a single functional mode and is operational when the power-supply voltage is greater than 2.7 V. The common-mode voltage must be between –16 V and +80 V. The maximum power supply voltage for the INA203-Q1 is 18 V.

Copyright © 2010–2016, Texas Instruments Incorporated

9 Application and Implementation

NOTE

Information in the following applications sections is not part of the TI component specification, and TI does not warrant its accuracy or completeness. TI's customers are responsible for determining suitability of components for their purposes. Customers should validate and test their design implementation to confirm system functionality.


9.1 Application Information

The INA203-Q1 device is designed to enable easy configuration for detecting overcurrent conditions and current monitoring in an application. This device is also incorporate two open-drain comparators with internal 0.6-V references. The comparator references can be overridden by external inputs. Comparator 1 includes a latching capability, and Comparator 2 has a user-programmable delay. The INA203-Q1 also provides a 1.2-V reference output. This device can also be paired with minimum additional devices to create more sophisticated monitoring functional blocks.

9.1.1 Basic Connections

Figure 30 shows the basic connections of the INA203-Q1. Connect the input pins, V_{IN+} and V_{IN-}, as closely as possible to the shunt resistor to minimize any resistance in series with the shunt resistance.

Power-supply bypass capacitors are required for stability. Applications with noisy or high-impedance power supplies may require additional decoupling capacitors to reject power-supply noise. Connect bypass capacitors close to the device pins.



Copyright © 2016, Texas Instruments Incorporated

Figure 30. INA203-Q1 Basic Connection

9.1.2 Selecting R_{SHUNT}

The value chosen for the shunt resistor, R_{SHUNT}, depends on the application and is a compromise between small-signal accuracy and maximum permissible voltage loss in the measurement line. High values of R_{SHUNT} provide better accuracy at lower currents by minimizing the effects of offset, while low values of R_{SHUNT} minimize voltage loss in the supply line. For most applications, best performance is attained with an R_{SHUNT} value that provides a full-scale shunt voltage range of 50 mV to 100 mV. Maximum input voltage for accurate measurements is (V_{SHUNT} – 0.25)/Gain.


Application Information (continued)

9.1.3 Input Filtering

An obvious and straightforward location for filtering is at the output of the INA203-Q1 series; however, this location negates the advantage of the low output impedance of the internal buffer. The only other option for filtering is at the input pins of the INA203-Q1, which is complicated by the internal 5 kΩ + 30% input impedance; this configuration is illustrated in Figure 31. Using the lowest possible resistor values minimizes both the initial shift in gain and effects of tolerance. Equation 2 gives the effect on initial gain:

$$\text{Gain Error \%} = 100 - \left(100 \times \frac{5\text{k}\Omega}{5\text{k}\Omega + R_{FILT}}\right) \quad (2)$$

To calculate the total effect on gain error, replace the 5-kΩ term with 5 kΩ – 30%, (or 3.5 kΩ) or 5 kΩ + 30% (or 6.5 kΩ). The tolerance extremes of R_{FILT} can also be inserted into the equation. If a pair of 100-Ω 1% resistors are used on the inputs, then the initial gain error will be 1.96%. Worst-case tolerance conditions will always occur at the lower excursion of the internal 5-kΩ resistor (3.5 kΩ), and the higher excursion of R_{FILT} + 3% in this case.



Copyright © 2016, Texas Instruments Incorporated

Figure 31. Input Filter

NOTE

The specified accuracy of the INA203-Q1 must then be combined in addition to these tolerances. While this discussion treated accuracy worst-case conditions by combining the extremes of the resistor values, it is appropriate to use geometric-mean or root-sum-square calculations to total the effects of accuracy variations.

9.1.4 Accuracy Variations as a Result of V_{SENSE} and Common-Mode Voltage

The accuracy of the INA203-Q1 current-shunt monitors is a function of two main variables: V_{SENSE} (V_{IN+} – $V_{IN–}$) and common-mode voltage, V_{CM}, relative to the supply voltage, V_S. V_{CM} is expressed as (V_{IN+} + $V_{IN–}$)/2; however, in practice, V_{CM} is seen as the voltage at V_{IN+} because the voltage drop across V_{SENSE} is usually small.

This section addresses the accuracy of these specific operating regions:

- Normal Case 1: $V_{SENSE} \geq 20$ mV, $V_{CM} \geq V_S$
- Normal Case 2: $V_{SENSE} \geq 20$ mV, $V_{CM} < V_S$
- Low V_{SENSE} Case 1: $V_{SENSE} < 20$ mV, $–16\text{ V} \leq V_{CM} < 0$
- Low V_{SENSE} Case 2: $V_{SENSE} < 20$ mV, $0\text{ V} \leq V_{CM} \leq V_S$
- Low V_{SENSE} Case 3: $V_{SENSE} < 20$ mV, $V_S < V_{CM} \leq 80$ V

Copyright © 2010–2016, Texas Instruments Incorporated

Application Information (continued)

9.1.4.1 Normal Case 1: V_{SENSE} ≥ 20 mV, V_{CM} ≥ V_S

This region of operation provides the highest accuracy. Here, the input offset voltage is characterized and measured using a two-step method. First, the gain is determined by Equation 3.

$$G = \frac{V_{OUT1} - V_{OUT2}}{100mV - 20mV} \quad (3)$$

where

- V_{OUT1} = output voltage with V_{SENSE} = 100 mV
- V_{OUT2} = output voltage with V_{SENSE} = 20 mV

Then the offset voltage is measured at V_{SENSE} = 100 mV and referred to the input (RTI) of the current shunt monitor, as shown in Equation 4.

$$V_{OS}\text{RTI (Referred-To-Input)} = \left[\frac{V_{OUT1}}{G}\right] - 100mV \quad (4)$$

In the *Typical Characteristics* section, the *Output Error vs Common-Mode Voltage* curve (Figure 7) shows the highest accuracy for this region of operation. In this plot, V_S = 12 V; for V_{CM} ≥ 12 V, the output error is at its minimum. This case is also used to create the V_{SENSE} ≥ 20 mV output specifications in the *Electrical Characteristics* table.

9.1.4.2 Normal Case 2: V_{SENSE} ≥ 20 mV, V_{CM} < V_S

This region of operation has slightly less accuracy than Normal Case 1 as a result of the common-mode operating area in which the part functions, as seen in the *Output Error vs Common-Mode Voltage* curve (Figure 7). As noted, for this graph V_S = 12 V; for V_{CM} < 12 V, the output error increases as V_{CM} becomes less than 12 V, with a typical maximum error of 0.005% at the most negative V_{CM} = –16 V.

9.1.4.3 Low V_{SENSE} Case 1:

V_{SENSE} < 20 mV, –16 V ≤ V_{CM} < 0; and

Low V_{SENSE} Case 3:


V_{SENSE} < 20 mV, V_S < V_{CM} ≤ 80 V

Although the INA203-Q1 is not designed for accurate operation in either of these regions, some applications are exposed to these conditions; for example, when monitoring power supplies that are switched on and off while V_S is still applied to the INA203-Q1. It is important to know what the behavior of the devices will be in these regions.

As V_{SENSE} approaches 0 mV, in these V_{CM} regions, the device output accuracy degrades. A larger-than-normal offset can appear at the current shunt monitor output with a typical maximum value of V_{OUT} = 300 mV for V_{SENSE} = 0 mV. As V_{SENSE} approaches 20 mV, V_{OUT} returns to the expected output value with accuracy as specified in the *Electrical Characteristics*. Figure 32 illustrates this effect (Gain = 100).

Copyright © 2010–2016, Texas Instruments Incorporated

Application Information (continued)




Data taken from INA205, a device of INA20x family with Gain = 100

Figure 32. Example for Low V_{SENSE} Cases 1 and 3 (Gain = 100)

9.1.4.4 Low V_{SENSE} Case 2: V_{SENSE} < 20 mV, 0 V ≤ V_{CM} ≤ V_S

This region of operation is the least accurate for the INA203-Q1. To achieve the wide input common-mode voltage range, this device uses two operational amplifiers (Opamp) front ends in parallel. One Opamp front end operates in the positive input common-mode voltage range, and the other in the negative input region. For this case, neither of these two internal amplifiers dominate and overall loop gain is very low. Within this region, V_{OUT} approaches voltages close to linear operation levels for Normal Case 2. This deviation from linear operation becomes greatest the closer V_{SENSE} approaches 0 V. Within this region, as V_{SENSE} approaches 20 mV, device operation is closer to that described by Normal Case 2. Figure 33 illustrates this behavior. The V_{OUT} maximum peak for this case is tested by maintaining a constant V_S, setting V_{SENSE} = 0 mV, and sweeping V_{CM} from 0 V to V_S. The exact V_{CM} at which V_{OUT} peaks during this test varies from part to part, but the V_{OUT} maximum peak is tested to be less than the specified V_{OUT} Tested Limit.



NOTE: (1) INA203-Q1 V_{OUT} Tested Limit = 0.4V.

Data taken from INA205, a device of INA20x family with Gain = 100

Figure 33. Example for Low V_{SENSE} Case 2 (Gain = 100)

Copyright © 2010–2016, Texas Instruments Incorporated


Application Information (continued)

9.1.5 Transient Protection

The –16 V to +80 V common-mode range of the INA203-Q1 is ideal for withstanding automotive fault conditions ranging from 12-V battery reversal up to 80-V transients, since no additional protective components are needed up to those levels. In the event that the INA203-Q1 is exposed to transients on the inputs in excess of their ratings, then external transient absorption with semiconductor transient absorbers (zeners or *Transzorbs*) are necessary. Use of metal oxide varistors (MOVs) or video disk recorders (VDRs) is not recommended except when they are used in addition to a semiconductor transient absorber. Select the transient absorber such that it will never allow the INA203-Q1 to be exposed to transients greater than 80 V (that is, allow for transient absorber tolerance, as well as additional voltage because of transient absorber dynamic impedance). Despite the use of internal zener-type ESD protection, the INA203-Q1 does not lend itself to using external resistors in series with the inputs because the internal gain resistors can vary up to ±30% but are closely matched. (If gain accuracy is not important, then resistors can be added in series with the INA203-Q1 inputs with two equal resistors on each input.)

9.2 Typical Applications

9.2.1 Polyswitch Warning and Fault Detection Circuit



Copyright © 2016, Texas Instruments Incorporated

Figure 34. Polyswitch Warning and Fault Detection Circuit Schematic

9.2.1.1 Design Requirements

The device measures current through a resistive shunt with current flowing in one direction, thus enabling detection of an overlimit or warning event only when the differential input voltage exceeds the corresponding threshold limits. When the current reaches the warning limit of 0.6 V, the output of CMP2 will transition high indicating a warning condition. When the current further increases to or past the overlimit limit of 1.2 V, the output of CMP1 will transition high indicating an overlimit condition. Optional C_{DELAY} can be sized to add delay to CMP2.

9.2.1.2 Detailed Design Procedure

Figure 34 shows the basic connections of the device. The input terminals, V_{IN+} and $V_{IN–}$, should be connected as close as possible to the current-sensing resistor or polymeric switch to minimize any resistance in series with the shunt resistance. Additional resistance between the current-sensing resistor and input terminals can result in errors in the measurement. When input current flows through this external input resistance, the voltage developed across the shunt resistor can differ from the voltage reaching the input terminals.

Typical Applications (continued)

9.2.1.3 Application Curves




Figure 35. Polyswitch Warning and Fault Detection Circuit Response





Figure 36. Polyswitch Warning and Fault Detection Circuit With Delay Response

9.2.2 Lead-Acid Battery Protection Circuit

See Figure 37 for a protection scheme using INA203-Q1 for a lead-acid battery application.



Copyright © 2016, Texas Instruments Incorporated

Figure 37. Lead-Acid Battery Protection Circuit Schematic

Copyright © 2010–2016, Texas Instruments Incorporated

10 Power Supply Recommendations

The input circuitry of the INA203-Q1 can accurately measure beyond the power-supply voltage, V_S. For example, the V_S power supply can be 5 V, whereas the load power-supply voltage is up to 80 V. The output voltage range of the OUT terminal, however, is limited by the voltages on the power-supply pin.

11 Layout

11.1 Layout Guidelines

- Connect the input pins to the sensing resistor using a Kelvin or 4-wire connection. This connection technique ensures that only the current-sensing resistor impedance is detected between the input pins. Poor routing of the current-sensing resistor commonly results in additional resistance present between the input pins. Given the very low ohmic value of the current resistor, any additional high-current carrying impedance can cause significant measurement errors.
- The power-supply bypass capacitor should be placed as closely as possible to the supply and ground pins. TI recommends the value of this bypass capacitor is 0.1 μF. Additional decoupling capacitance can be added to compensate for noisy or high-impedance power supplies.

11.2 Layout Example




Figure 38. Layout Recommendation

12 器件和文档支持

12.1 社区资源

The following links connect to TI community resources. Linked contents are provided "AS IS" by the respective contributors. They do not constitute TI specifications and do not necessarily reflect TI's views; see TI's Terms of Use.

TI E2E™ Online Community ***TI's Engineer-to-Engineer (E2E) Community.*** Created to foster collaboration among engineers. At e2e.ti.com, you can ask questions, share knowledge, explore ideas and help solve problems with fellow engineers.

Design Support ***TI's Design Support*** Quickly find helpful E2E forums along with design support tools and contact information for technical support.

12.2 商标

E2E is a trademark of Texas Instruments.
All other trademarks are the property of their respective owners.

12.3 静电放电警告



这些装置包含有限的内置 ESD 保护。 存储或装卸时，应将导线一起截短或将装置放置于导电泡棉中，以防止 MOS 门极遭受静电损伤。

12.4 Glossary

SLYZ022 — *TI Glossary*.

This glossary lists and explains terms, acronyms, and definitions.

13 机械、封装和可订购信息

以下页中包括机械、封装和可订购信息。这些信息是针对指定器件可提供的最新数据。这些数据会在无通知且不对本文档进行修订的情况下发生改变。要获得这份数据表的浏览器版本，请查阅左侧的导航栏。

版权 © 2010–2016, Texas Instruments Incorporated

PACKAGING INFORMATION

Orderable Device	Status (1)	Package Type	Package Drawing	Pins	Package Qty	Eco Plan (2)	Lead finish/ Ball material (6)	MSL Peak Temp (3)	Op Temp (°C)	Device Marking (4/5)	Samples
INA203AQPWRQ1	ACTIVE	TSSOP	PW	14	2000	RoHS & Green	NIPDAU	Level-2-260C-1 YEAR	-40 to 125	I203AQ	Samples

(1) The marketing status values are defined as follows:
ACTIVE: Product device recommended for new designs.
LIFEBUY: TI has announced that the device will be discontinued, and a lifetime-buy period is in effect.
NRND: Not recommended for new designs. Device is in production to support existing customers, but TI does not recommend using this part in a new design.
PREVIEW: Device has been announced but is not in production. Samples may or may not be available.
OBSOLETE: TI has discontinued the production of the device.

(2) **RoHS:** TI defines "RoHS" to mean semiconductor products that are compliant with the current EU RoHS requirements for all 10 RoHS substances, including the requirement that RoHS substance do not exceed 0.1% by weight in homogeneous materials. Where designed to be soldered at high temperatures, "RoHS" products are suitable for use in specified lead-free processes. TI may reference these types of products as "Pb-Free".
RoHS Exempt: TI defines "RoHS Exempt" to mean products that contain lead but are compliant with EU RoHS pursuant to a specific EU RoHS exemption.
Green: TI defines "Green" to mean the content of Chlorine (Cl) and Bromine (Br) based flame retardants meet JS709B low halogen requirements of <=1000ppm threshold. Antimony trioxide based flame retardants must also meet the <=1000ppm threshold requirement.

(3) MSL, Peak Temp. - The Moisture Sensitivity Level rating according to the JEDEC industry standard classifications, and peak solder temperature.

(4) There may be additional marking, which relates to the logo, the lot trace code information, or the environmental category on the device.

(5) Multiple Device Markings will be inside parentheses. Only one Device Marking contained in parentheses and separated by a "~" will appear on a device. If a line is indented then it is a continuation of the previous line and the two combined represent the entire Device Marking for that device.


(6) Lead finish/Ball material - Orderable Devices may have multiple material finish options. Finish options are separated by a vertical ruled line. Lead finish/Ball material values may wrap to two lines if the finish value exceeds the maximum column width.

Important Information and Disclaimer: The information provided on this page represents TI's knowledge and belief as of the date that it is provided. TI bases its knowledge and belief on information provided by third parties, and makes no representation or warranty as to the accuracy of such information. Efforts are underway to better integrate information from third parties. TI has taken and continues to take reasonable steps to provide representative and accurate information but may not have conducted destructive testing or chemical analysis on incoming materials and chemicals. TI and TI suppliers consider certain information to be proprietary, and thus CAS numbers and other limited information may not be available for release.


In no event shall TI's liability arising out of such information exceed the total purchase price of the TI part(s) at issue in this document sold by TI to Customer on an annual basis.

TAPE AND REEL INFORMATION

REEL DIMENSIONS




TAPE DIMENSIONS



A0	Dimension designed to accommodate the component width
B0	Dimension designed to accommodate the component length
K0	Dimension designed to accommodate the component thickness
W	Overall width of the carrier tape
P1	Pitch between successive cavity centers


QUADRANT ASSIGNMENTS FOR PIN 1 ORIENTATION IN TAPE



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Reel Diameter (mm)	Reel Width W1 (mm)	A0 (mm)	B0 (mm)	K0 (mm)	P1 (mm)	W (mm)	Pin1 Quadrant
INA203AQPWRQ1	TSSOP	PW	14	2000	330.0	12.4	6.9	5.6	1.6	8.0	12.0	Q1


TAPE AND REEL BOX DIMENSIONS



*All dimensions are nominal

Device	Package Type	Package Drawing	Pins	SPQ	Length (mm)	Width (mm)	Height (mm)
INA203AQPWRQ1	TSSOP	PW	14	2000	367.0	367.0	35.0


PW (R–PDSO–G14) PLASTIC SMALL OUTLINE



4040064–3/G 02/11

NOTES:
A. All linear dimensions are in millimeters. Dimensioning and tolerancing per ASME Y14.5M–1994.
B. This drawing is subject to change without notice.
C. Body length does not include mold flash, protrusions, or gate burrs. Mold flash, protrusions, or gate burrs shall not exceed 0,15 each side.
D. Body width does not include interlead flash. Interlead flash shall not exceed 0,25 each side.
E. Falls within JEDEC MO–153

PW (R–PDSO–G14) PLASTIC SMALL OUTLINE



NOTES:
A. All linear dimensions are in millimeters.
B. This drawing is subject to change without notice.
C. Publication IPC–7351 is recommended for alternate designs.
D. Laser cutting apertures with trapezoidal walls and also rounding corners will offer better paste release. Customers should contact their board assembly site for stencil design recommendations. Refer to IPC–7525 for other stencil recommendations.
E. Customers should contact their board fabrication site for solder mask tolerances between and around signal pads.

重要声明和免责声明

TI“按原样”提供技术和可靠性数据（包括数据表）、设计资源（包括参考设计）、应用或其他设计建议、网络工具、安全信息和其他资源，不保证没有瑕疵且不做出任何明示或暗示的担保，包括但不限于对适销性、某特定用途方面的适用性或不侵犯任何第三方知识产权的暗示担保。

这些资源可供使用 TI 产品进行设计的熟练开发人员使用。您将自行承担以下全部责任：(1) 针对您的应用选择合适的 TI 产品，(2) 设计、验证并测试您的应用，(3) 确保您的应用满足相应标准以及任何其他功能安全、信息安全、监管或其他要求。

这些资源如有变更，恕不另行通知。TI 授权您仅可将这些资源用于研发本资源所述的 TI 产品的应用。严禁对这些资源进行其他复制或展示。您无权使用任何其他 TI 知识产权或任何第三方知识产权。您应全额赔偿因在这些资源的使用中对 TI 及其代表造成的任何索赔、损害、成本、损失和债务，TI 对此概不负责。

TI 提供的产品受 TI 的销售条款或 ti.com 上其他适用条款/TI 产品随附的其他适用条款的约束。TI 提供这些资源并不会扩展或以其他方式更改 TI 针对 TI 产品发布的适用的担保或担保免责声明。

TI 反对并拒绝您可能提出的任何其他或不同的条款。

邮寄地址：Texas Instruments, Post Office Box 655303, Dallas, Texas 75265
Copyright © 2022，德州仪器 (TI) 公司